

## QUICKCLOSE CORE Library update for HP49G+/49G and HP48Gii

### Instructions for updating Quickclose Core

1. On the HP49G+/G/48Gii, press **[VAR]**
2. Press the **| DELB |** menu key
3. At the ***"Remove CORE Library? (Data is saved)"*** prompt, press **| YES |**
4. If the PLUS library is also installed, press NO at the "Remove PLUS Library?" prompt.
5. Connect the USB cable to the PC and the calculator
6. On the calculator, press **[Right-Shift] [>]**
7. ***"Xmodem Server Waiting for command"*** should be displayed
8. On the PC, run the HP Connectivity software,
9. Ensure that the displayed parameters are **"Auto"** or **"HPx9G+"** and **115200** baud
10. Click on **File, Connect** and then Click on the **OK** button in the HP Connectivity window.
11. Copy and paste the downloaded update library **QC3NEW.LIB** on to the calculator
12. Shutdown the HP Connectivity software (press the **X** in the top left of the window)
13. On the calculator press the **| QCLOS |** menu key (press the VAR key first if it is not displayed)
14. Press **[NXT]**
15. Press the **| RELOD |** menu key
16. Press **| RUN |** to run the updated CORE program. All data, settings and activation codes are preserved.